

## Motion detecting with corridor function

- This luminaire is integrated with
- Motion Detecting with Corridor function

Detecting distance	Lighting timer				Light sensitivity				Timer on dimmed light				Dimmed light	
	S1	S2	S3	S4	S5	S6	S7	S8	S9	S10	S11	S12	S13	S14
1.0-2.0 meters	OFF	OFF	10S	OFF	OFF	24H	OFF	OFF	24H	OFF	OFF	10%	OFF	
2.5-3.5meters	OFF	ON	1M	OFF	ON	10LUX	OFF	ON	15S	OFF	ON	30%	ON	
4.5-5.5 meters	ON	ON	3M	ON	OFF	30LUX	ON	OFF	30M	ON	OFF			
			5M	ON	ON	50LUX	ON	ON	60M	ON	ON			

### Motion Detection

#### The default setting:

Light sensitivity: 10 Lux

Detecting sensitivity: 4.5-5.5M

Lighting timer: 1 minutes (100%)

Timer on dimmed light: 60 minutes (30%)

You may configure your luminaires according to your needs before or after the installation of the luminaires.



How to configure with different combination



9 8 7 6 5 4 3 2 1 0  
 ON 1

- Open the lid
- Set the switch according to table 1
- Close the lid